

## Technical Data Bulletin

# N880BNC1

800 MHz Quarterwave Antenna, with Urethane Radome with BNC male connector.



## Specifications

### Electrical

Frequency Range:	869 MHz to 894 MHz
Bandwidth:	25 MHz
Gain:	2.15 dBi
VSWR:	2.0:1
Impedance:	50 Ohms
Polarization:	Vertical

### Mechanical

Connector:	BNC male
Length:	3.5 Inches (Nominal)
Radome Material:	Urethane Sleeve
Colors:	N880BNC1B (Black) other colors available on special request
Special Features:	Quarterwave Design requires a ground- plane.

# Antenna-Sales.com