

Technical Data Bulletin NEC880BNC1

Economy 800 MHz Quarterwave Antenna with BNC male connector.



Specifications

Electrical

| | |
|------------------|--------------------|
| Frequency Range: | 869 MHz to 894 MHz |
| Bandwidth: | 26 MHz |
| Gain: | 2.15 dBi |
| VSWR: | 1.5:1 |
| Impedance: | 50 Ohms |
| Polarization: | Vertical |

Mechanical

| | |
|-------------------|---|
| Connector: | BNC male |
| Length: | 3.5 Inches (Nominal) |
| Radome Material: | Polyolefin Tube |
| Colors: | NEC880BNC1B (Black) other colors available on special request |
| Special Features: | Quarterwave Design requires a ground- plane. |

Antenna-Sales.com